

## AMILO Li 1718

### Large package for little money

Issue August 2007

Pages 3

Imagine your next holiday: With the AMILO Li 1718 on your side you can enjoy your favorite music on the terrace of your holiday apartment. It is raining? Look forward to your 15.4-inch, crystal clear home cinema, your latest DVDs, popcorn and coke. You miss your friends? With the integrated Wireless LAN you can chat with them or write them an e-mail and attach the pictures of your wonderful holiday. You want to go out? Go online and check the Internet, which restaurant would be the best for your special taste.

With the AMILO Li 1718 you have a basic but reliable mobile solution, whether you are at home or on the move.

#### Features

- Intel® mobile technology with Intel® Core™ 2 Duo, Intel® Core™ Duo, Intel® Pentium Dual Core™ or Intel® Celeron® M Processor
- 15.4" TFT WXGA display with BrilliantView technology for amazing luscious colors
- ATI Radeon® Xpress 200M (shared graphics) up to 256MB HyperMemory™
- 4 USB ports provide you with outstanding connection options
- Built-in Multi format DVD burner with double layer support to enjoy your films and music on the move
- Up to 2GB DDR2 SDRAM in two memory SO-DIMM slots
- Windows Vista® Home Basic or Windows Vista® Home Premium and Application Software



---

**Operating system**

Windows Vista® Home Basic or  
Windows Vista® Home Premium<sup>1</sup>

**Fujitsu Siemens Computers recommends  
Windows Vista® Home Premium****Optional Application Software**

Microsoft® Works  
Nero 7 Essentials (CD/DVD burning Software)  
Adobe Reader  
Norton Internet Security Suite or Norman Anti-Virus  
Country specific Internet Service Providers

Manual, Safety Guide and Warranty Guide

---

**Drivers and Utility**

Drivers and Utility DVD included (optional)  
Updates downloadable at  
<http://www.fujitsu-siemens.com>

---

**System, processor, architecture**

Chipset: ATI RC415ME + SB460

CPU: Intel® Celeron® M processors with 533MHz FSB:  
- Celeron® M 430 / 1.73GHz / 1MB 2<sup>nd</sup> level cache  
- Celeron® M 440 / 1.86GHz / 1MB 2<sup>nd</sup> level cache  
- Celeron® M 520 / 1.6GHz / 1MB 2<sup>nd</sup> level cache

Intel® Pentium Dual Core™ processor with  
533MHz FSB  
- T2060 / 1.6GHz / 1MB 2<sup>nd</sup> level cache

Intel® Core™ Duo processors with 533 MHz FSB  
- T2350 / 1.86GHz / 2MB 2<sup>nd</sup> level cache

Intel® Core™ 2 Duo processors with 667MHz FSB  
- T5300 / 1.73GHz / 2MB 2<sup>nd</sup> level cache  
- T5500 / 1.66GHz / 2MB 2<sup>nd</sup> level cache

---

**Memory**

2 SO-DIMM memory slots (no memory on board)  
512MB DDR2 533/667MHz  
1GB DDR2 533/667MHz

---

**Storage devices / drives****HDD:**

80, 120 and 160GB SATA (5400rpm) hard disk

**ODD:**

8x Multi-format DVD burner with double layer  
- Read speed: CD-ROM 24x, DVD-ROM 8x  
- Write speed: CD-R 24x, CD-RW 16x, DVD+R 8x, DVD-R  
8x, DVD+RW 6x, DVD-RW 6x, DVD+R DL  
(Double Layer 8.5GB) 2,4x, DVD-R DL  
(Double Layer 8.5GB) 4x

---



---

**Display**

BrilliantView

Panel size: 15.4" TFT WXGA, 1280 x 800 pixel  
Compliance with standards ISO 13406-2 Class II

---

**ACPI functions**

S1 stand by (LCD off)  
S3 save to RAM  
S4 save to disk  
S5 soft off

---

**Graphics**

ATI Radeon Xpress 200M  
with up to 256MB HyperMemory™

---

**I/O Interfaces**

4x USB (version 2.0)  
1x VGA (VESA compatible)  
1x DC-In  
1x RJ11 for modem 56 Kbps (.V92)  
1x RJ45 for LAN (10/100)  
1x line out shared with headphone out (stereo)  
1x line in shared with microphone in (mono)

---

**Communications**

Built-in 56Kbps, .V92 fax modem (MDC 1.5)  
10/100Mbps LAN  
Integrated wireless LAN (WLAN) solution 802.11b/g  
Speeds up to 54Mbps  
Industry standard wireless LAN security support  
Excellent performance through per packet antenna  
selection  
For use in BE, CH, DK, DE, EE, FI, FR, EL, IE, IS,  
IT, LI, LV, LT, LU, MT, NL, NO, PL, AT, PT, SE, SK,  
ES, CZ, HU, UK, CY, NL

---

---

**Audio**

Support of HD audio for SP/DIF output with up to 7.1 channels, 1 built-in high quality speaker, microphone in combined with stereo line-in, headphone out shared with line-out, sound volume controlled by Hot Keys

---

**Launch Keys**

launch the following applications:

- WLAN on/off
- Internet browser
- Silent mode (reduce noise level / fan speed, by reducing the CPU & VGA performance)
- Power on

---

**Hot Keys**

The notebook uses hotkeys or key combinations for:

- Fn-F3 Mute
- Fn-F4 Display toggle, switches display output between display screen and external monitor or to dual view
- Fn-F5 raise volume
- Fn-F6 reduce volume
- Fn-F7 raise display brightness
- Fn-F8 reduce display brightness

---

**Pointing devices & control buttons**

Touchpad with a left and right mouse button  
Power button / lid switch

---

**Security**

User and supervisor password  
Kensington Lock

---



---

**Power system**

Li-Ion battery 3 cells, 11.1V / 4400mAh  
Approximately 1h battery runtime, depending upon usage<sup>1</sup>  
or

Li-Ion battery 6 cells, 11.1V / 4400mAh  
Approximately 2.5hrs battery runtime, depending upon usage<sup>1</sup>

Dynamic charge supported, ACPI 2.0 supported  
External universal AC adapter: 110 – 240 V AC, 50 - 60Hz, output: 65 / 90W<sup>2</sup> with 20V DC

---

**Dimensions and weight**

355mm (W) x 255.8mm (D) x 24 – 34mm (H)  
Approximately: 2.7 kg<sup>3</sup>

---

**Operating conditions**

operational: 15° - 35°C (ambient temperature)  
10% to 90% relative humidity, non-condensing

---

**Certifications**

CE Marking  
R&TTE (WLAN)

---

**Warranty**

Country specific terms

---

**Accessories (optional)**

AC adapter  
2<sup>nd</sup> battery  
Car charger  
USB Floppy Drive  
Carrying Devices

---

- 1) Depending on configuration.
- 2) Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Recharge time varies depending on usage. The recharge capacity may diminish after some months so that the battery lifetime as well as operating time can not be assured.
- 3) AC Adapter output depends on actual configuration.
- 4) Weight may vary depending on actual configuration.